

PROWORD

MEANING

WORD BEFORE	The word of the message to which I have reference is that which precedes.
WORDS TWICE	Transmit each word or group twice.
WRONG	Your last transmission was incorrect.

5. AUTHENTICATION

- a. The challenge is any two letters in alphabet but ZULU, preceded by the proword AUTHENTICATE.

EXAMPLE: D7C46R-THIS IS H8Q46R-AUTHENTICATE-ALPHA XRAY-OVER


- b. The reply is similarly transmitted, preceded by the proword I AUTHENTICATE . It may be followed by a counter challenge.

EXAMPLE: H8Q46R-THIS-IS-D7C46R-I-AUTHENTICATE-TANGO-OVER

THE ENEMY IS ALWAYS LISTENING

☆ GPO : 1993 - 362-919

GTA 11-1-7



SEND A RADIO MESSAGE

**MOS 31C
31K**

DISTRIBUTION: U.S. Army training and audiovisual support centers (TASCs)

Approved for public release; distribution is unlimited

HEADQUARTERS, DEPARTMENT OF THE ARMY

JUNE 1987

SUPERSEDES GTA 11-1-1

1. GENERAL INSTRUCTIONS

- Write or plan message before transmitting.
- Listen before transmitting.
- Speak clearly and slowly.

2. PHONETICS

- a. Phonetic alphabet.

a ALFA	J JULIETT	S SIERRA
B BRAVO	K KILO	T TANGO
C CHARLIE	L LIMA	U UNIFORM
D DELTA	M MIKE	V VICTOR
E ECHO	N NOVEMBER	W WHISKEY
F FOXTROT	O OSCAR	X XRAY
G GOLF	P PAPA	Y YANKEE
H HOTEL	Q QUEBEC	Z ZULU
I INDIA	R ROMEO	

- b. Phonetic pronunciation of numerals:

0 ZERO	4 FO-WER	7 SEVEN
1 WUN	5 FIFE	8 AIT
2 TOO	6 SIX	9 NINER
3 TREE		

- c. Transmit numbers digit by digit, except in the case of even thousands.

EXAMPLE: 136 WUN TREE SIX
500 FIFE ZERO ZERO
16000 WUN SIX THOUSAND

- Difficult or unusual words may be spelled using the phonetic alphabet preceeded by the proword I SPELL. IF pronounceable the word is pronounced before the proword I SPELL and immediately following the phonetic spelling of the word.
- STATION IDENTIFICATION - Stations are identified by letter-number-letter call signs obtained from the unit CEOI. The letters and numbers are spoken phonetically.
- TIME - The originators' time of any message (DTG) is always spoken phonetically.

3. TRANSMISSION FORMAT

16 Line radiotelephone transmission format.

- LINE 1. Not used in radio telephone
- LINE 2. Call sign of station(s) being called
- LINE 3. THIS IS followed by call sign of calling station
- LINE 4. Transmission instructions (eg RELAY TO)
- LINE 5. Preedence and originators time (DTG)
- LINE 6. FROM followed by call sign of originator
- LINE 7. TO followed by call sign of action addressee
- LINE 8. INFO followed by call sign of information addressee
- LINE 9. EXEMPT followed by call sign of exempt addressee
- LINE 10. GROUPS group count if needed
- LINE 11. BREAK
- LINE 12. TEXT (plain language, code or cipher groups)
- LINE 13. BREAK
- LINE 14. TIME (used only if no DTG on line 5)
- LINE 15. Final instructions eg. CORRECTION, WAIT, WAIT OUT, MORE TO FOLLOW, AUTHENTICATION IS
- LINE 16. Terminating proword eg. OVER or OUT

EXAMPLE: D7C46R-THIS IS-B8Q46R-MESSAGE-PRIORITY-TIME-2011537Z-FROM-H8Q46-TO-D7C46-BREAK-NEED AMMO ASAP-BREAK-OVER

PROWORD

MEANING

4. PROWORDS

Prowords are pronounceable words or phrases which have been assigned meanings for the purpose of expediting message handling on radiotelephone circuits.

CORRECTION

An error has been made in this transmission. Transmission will continue with the last word correctly transmitted.

An error has been made in this transmission (or message indicated). The correct version is

DISREGARD THIS TRANSMISSION-OUT

This transmission is in error. Disregard it. This proword will not be used to cancel a completed transmission.

DO NOT ANSWER

Station(s) called are not to answer this call. When this proword is used the transmission will not be recognized.

EXEMPT

The call sign(s) which / that follow(s) is / are exempted.

FIGURES

Numbers follow.

FLASH

Precedence FLASH.

FROM

The call sign which follows is the originators.

GROUPS

This message contains the number of groups indicated.

PROWORD	MEANING
ALL AFTER	The portion of the message to which I have reference is all that which follows.
ALL BEFORE	The portion of the message to which I have reference is all that which precedes.
AUTHENTICATION	The station called is to reply to the challenge which follows.
AUTHENTICATION IS	The transmission authentication of this message is
BREAK	I hereby indicate the separation of the text from other portions of the message.
CORRECT	You are correct, or what you have transmitted is correct.

PROWORD	MEANING	PROWORD	MEANING
I AUTHENTICATE	The following is the replay to your challenge.	ROGER	I have received your last transmission satisfactorily.
IMMEDIATE	Precedence IMMEDIATE.	ROUTINE	Precedence ROUTINE.
INFO	The call sign(s) which / that follow(s) is/ are that of the information addressee(s).	SAY AGAIN	Repeat all of your last transmission. Followed by identification data means repeat that portion of.
I READ BACK	The following is my response to your instructions to READ BACK.	SPEAK SLOWER	Your transmission is at too fast a speed. Reduce speed of transmission.
I SAY AGAIN	I am repeating transmission or portion indicated.	THIS IS	This transmission is from the station whose call sign follows.
I SPELL	I shall spell the next word phonetically.	TIME	That which follows is the time or date time group of the message.
MESSAGE	A message which requires recording follows.	TO	The call sign(s) which / that follow(s) is/ are that of the action addressee(s).
OUT	This is the end of my transmission to you and no answer is required.	UNKNOWN STATION	The identity of the station with whom I am attempting to communicate is unknown.
OVER	This the end of my transmission to you and a response is necessary.	WAIT	I must pause a few seconds.
PRIORITY	Precedence PRIORITY.	WAIT OUT	I must pause longer than a few seconds.
READ BACK	Repeat this entire transmission back to me exactly as received.	WORD AFTER	The word of the message to which I have reference is that which follows.
RELAY (TO)	Transmit this message to all addressees.		